

Temperature of soldering iron with a diameter 1.6 x 5 mm piece of solder applied once every 3 seconds to paper phenol copper board.

Lead-free solder is used

Detach the control knob and lock the temperature setting.







Turn the CAL knob to attain a more accurate temperature.



* Accurate temperature control can be performed even outside the scale.

Cm	aaifi	antic	
Sp	eciii	catic	DNS

Specifications				
Model No.	FX-600	FX-601		
Power consumption	50 W	47 W		
Temperature range	200 to 500°C	240 to 540°C		
Temperature stability	±1°C at idle temperature	±1°C at idle temperature		
Tip to ground resistance	<2 Ω	<2 Ω		
Tip to ground potential	<2 mV	<2 mV		
Heating element	Ceramic heater	Ceramic heater		
Standard tip	Shape-B (No. T18-B)	Shape-2B (No. T19-B2)		
Total length*	233 mm (with B tip)	237 mm (with 2B tip)		
Weight*	61 g (with B tip)	68 g (with 2B tip)		
* Without cord				

30