



## NADITBNC-FX

Female XLR cable end 110  $\Omega$  input - female BNC 75  $\Omega$  output. Interface balanced and coaxial lines.

### Features & Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match balanced to coaxial lines
- Match impedances 110  $\Omega$  to 75  $\Omega$
- Simple to use, passive units

Technical Information

Product	
Title	NADITBNC-FX
Connection Type	Adapter
Gender	female

Electrical	
Frequencyrange	0.1 - 6 MHz
Rated voltage	$\leq 5\text{ V p-p}$
VSWR	$< 1.1$
Return loss	$> 26.4\text{ dB}$
Insertion Loss	$< 0.3\text{ dB @ } 0.1\text{ MHz to } 10\text{ MHz}$

Mechanical	
Wiresize	