



## Constant Current RGB/White LED Driver with I<sup>2</sup>C Control

#### **Features**

- Ultra low dropout regulated current sinks
  - 3-Channels: KTD2026
  - 4-Channels: KTD2027
- 40mV typical at 10mA per channel
- Programmable LED setting using I<sup>2</sup>C control
- Individual channel control
  - On/Off Interval Time Control
  - Dimming Up/Down Time
  - Current Level Setting
  - ► RGB or RGBW LED Color Control
- 192 current levels: 24mA max, 0.125mA step
- ±5% current matching for max current
- Low supply current of 200µA typ.
- No noise, non-pulsating LED current
- Fast, smooth start-up
- VIN Range: 2.7V to 5.5V
- 0.1µA Shutdown Current
- Pb-free Package: UTDFN-8 1.5x1.5mm
- -40°C to +85°C Temperature Range

#### **Applications**

- RGB indicator LEDs
- Flashing LEDs
- Mobile Phones
- Handheld Devices
- Digital Cameras

### **Typical Application**

#### **Brief Description**

The KTD2026/7 are fully programmable, constant current RGB or RGBW LED drivers with a flexible control interface. The devices are ideally powered from one-cell lithiumion/polymer, 3-cell NiCd/NiMH/Alkaline batteries, or systems with 3.3V or 5V supplies. The independent programmable constant current sinks operate without external components.

With an on-chip timing control unit, LED blink rate, fade-in and fade-out are user-adjustable resulting in unique color lighting patterns.

Ten internal registers are programmed via the I<sup>2</sup>C interface with a built-in decoder allowing individual control of the three/four LED channels' On/Off state and current level. A total of 192 current levels are available for each channel from 0.125mA to 24mA with a 0.125mA step.

In shutdown mode, the quiescent current is reduced to less than  $1\mu A.$ 

The driver is available in a low profile 8-pin 1.5mm x 1.5mm x 0.5mm Ultra-Thin DFN package. The packages are Pb-free and RoHS compliant.





## **Ordering Information**

| Part Number    | IOUT max<br>Per channel | I <sup>2</sup> C Device<br>Address | Marking <sup>1</sup> | Operating<br>Temperature | Package        |
|----------------|-------------------------|------------------------------------|----------------------|--------------------------|----------------|
| KTD2026EWE-TR  | 24mA                    | 30h                                | ETYYZ                | -40°C to +85°C           | UTDFN1.5x1.5-8 |
| KTD2026BEWE-TR | 24mA                    | 31h                                | GKYYZ                | -40°C to +85°C           | UTDFN1.5x1.5-8 |
| KTD2026CEWE-TR | 24mA                    | 32h                                | LYYYZ                | -40°C to +85°C           | UTDFN1.5x1.5-8 |
| KTD2027EWE-TR  | 24mA                    | 30h                                | ESYYZ                | -40°C to +85°C           | UTDFN1.5x1.5-8 |
| KTD2027BEWE-TR | 24mA                    | 31h                                | LZYYZ                | -40°C to +85°C           | UTDFN1.5x1.5-8 |

1. "YYZ" is the date code and assembly code.

Kinetic Technologies cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Kinetic Technologies product. No intellectual property or circuit patent licenses are implied. Kinetic Technologies reserves the right to change the circuitry and specifications without notice at any time.

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

KID2027EWE-TR KTD2026BEWE-TR KTD2026EWE-TR