



ALPHA & OMEGA
SEMICONDUCTOR

AO3413



20V P-Channel MOSFET

General Description

The AO3413 uses advanced trench technology to provide excellent $R_{DS(ON)}$, low gate charge and operation with gate voltages as low as 1.8V. This device is suitable for use as a load switch or in PWM applications.

Features

$V_{DS} = -20V$	
$I_D = -3A$	($V_{GS} = -4.5V$)
$R_{DS(ON)} < 80m\Omega$	($V_{GS} = -4.5V$)
$R_{DS(ON)} < 100m\Omega$	($V_{GS} = -2.5V$)
$R_{DS(ON)} < 130m\Omega$	($V_{GS} = -1.8V$)



Absolute Maximum Ratings $T_A=25^\circ C$ unless otherwise noted

Parameter	Symbol	Maximum	Units
Drain-Source Voltage	V_{DS}	-20	V
Gate-Source Voltage	V_{GS}	± 8	V
Continuous Drain Current ^A	I_D	-3	A
$T_A=70^\circ C$		-2.4	
Pulsed Drain Current ^B	I_{DM}	-15	
Power Dissipation ^A	P_D	1.4	W
$T_A=70^\circ C$		0.9	
Junction and Storage Temperature Range	T_J, T_{STG}	-55 to 150	°C

Thermal Characteristics

Parameter	Symbol	Typ	Max	Units
Maximum Junction-to-Ambient ^A	$R_{\theta JA}$	70	90	°C/W
Steady-State		100	125	°C/W
Maximum Junction-to-Lead ^C	$R_{\theta JL}$	63	80	°C/W

Electrical Characteristics ($T_J=25^\circ\text{C}$ unless otherwise noted)

Symbol	Parameter	Conditions	Min	Typ	Max	Units
BV_{DSS}	Drain-Source Breakdown Voltage	$I_D=-250\mu\text{A}, V_{GS}=0\text{V}$	-20			V
I_{DSS}	Zero Gate Voltage Drain Current	$V_{DS}=-20\text{V}, V_{GS}=0\text{V}$ $T_J=55^\circ\text{C}$			-1 -5	μA
I_{GSS}	Gate-Body leakage current	$V_{DS}=0\text{V}, V_{GS}=\pm 8\text{V}$			± 100	nA
$V_{\text{GS(th)}}$	Gate Threshold Voltage	$V_{DS}=V_{GS}, I_D=-250\mu\text{A}$	-0.4	-0.65	-1	V
$I_{\text{D(ON)}}$	On state drain current	$V_{GS}=-4.5\text{V}, V_{DS}=-5\text{V}$	-15			A
$R_{\text{DS(ON)}}$	Static Drain-Source On-Resistance	$V_{GS}=-4.5\text{V}, I_D=-3\text{A}$ $T_J=125^\circ\text{C}$		56	80	$\text{m}\Omega$
		$V_{GS}=-2.5\text{V}, I_D=-2.6\text{A}$		70	100	$\text{m}\Omega$
		$V_{GS}=-1.8\text{V}, I_D=-1\text{A}$		85	130	$\text{m}\Omega$
g_{FS}	Forward Transconductance	$V_{DS}=-5\text{V}, I_D=-3\text{A}$		12		S
V_{SD}	Diode Forward Voltage	$I_S=-1\text{A}, V_{GS}=0\text{V}$		-0.7	-1	V
I_S	Maximum Body-Diode Continuous Current				-1.4	A

DYNAMIC PARAMETERS

C_{iss}	Input Capacitance	$V_{GS}=0\text{V}, V_{DS}=-10\text{V}, f=1\text{MHz}$		560	745	pF
C_{oss}	Output Capacitance			80		pF
C_{rss}	Reverse Transfer Capacitance			70		pF
R_g	Gate resistance	$V_{GS}=0\text{V}, V_{DS}=0\text{V}, f=1\text{MHz}$		15	23	Ω

SWITCHING PARAMETERS

Q_g	Total Gate Charge	$V_{GS}=-4.5\text{V}, V_{DS}=-10\text{V}, I_D=-3\text{A}$		8.5	11	nC
Q_{gs}	Gate Source Charge			1.2		nC
Q_{gd}	Gate Drain Charge			2.1		nC
$t_{D(\text{on})}$	Turn-On DelayTime	$V_{GS}=-4.5\text{V}, V_{DS}=-10\text{V}, R_L=3.3\Omega, R_{\text{GEN}}=6\Omega$		7.2		ns
t_r	Turn-On Rise Time			36		ns
$t_{D(\text{off})}$	Turn-Off DelayTime			53		ns
t_f	Turn-Off Fall Time			56		ns
t_{rr}	Body Diode Reverse Recovery Time		$I_F=-3\text{A}, dI/dt=100\text{A}/\mu\text{s}$	37	49	ns
Q_{rr}	Body Diode Reverse Recovery Charge	$I_F=-3\text{A}, dI/dt=100\text{A}/\mu\text{s}$		27		nC

A: The value of R_{QA} is measured with the device mounted on 1 in² FR-4 board with 2oz. copper, in a still air environment with $T_A=25^\circ\text{C}$. The value in any given application depends on the user's specific board design. The current rating is based on the $t \leq 10\text{s}$ thermal resistance rating.

B: Repetitive rating, pulse width limited by junction temperature.

C. The R_{QA} is the sum of the thermal impedance from junction to lead R_{QJL} and lead to ambient.

D. The static characteristics in Figures 1 to 6 are obtained using 300 μs pulse width, duty cycle 0.5% max.







E. These tests are performed with the device mounted on 1 in² FR-4 board with 2oz. Copper, in a still air environment with $T_A=25^\circ\text{C}$. The SOA curve provides a single pulse rating.

APPLICATIONS OR USES AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS ARE NOT AUTHORIZED. AOS DOES NOT ASSUME ANY LIABILITY ARISING OUT OF SUCH APPLICATIONS OR USES OF ITS PRODUCTS. AOS RESERVES THE RIGHT TO MAKE CHANGES TO PRODUCT SPECIFICATIONS WITHOUT NOTICE. IT IS THE RESPONSIBILITY OF THE CUSTOMER TO EVALUATE SUITABILITY OF THE PRODUCT FOR THEIR INTENDED APPLICATION. CUSTOMER SHALL COMPLY WITH APPLICABLE LEGAL REQUIREMENTS, INCLUDING ALL APPLICABLE EXPORT CONTROL RULES, REGULATIONS AND LIMITATIONS.

AOS' products are provided subject to AOS' terms and conditions of sale which are set forth at:
http://www.aosmd.com/terms_and_conditions_of_sale



TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS





TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS




Figure 7: Gate-Charge Characteristics




Figure 8: Capacitance Characteristics




Figure 9: Maximum Forward Biased Safe Operating Area (Note E)




Figure 10: Single Pulse Power Rating Junction-to-Ambient (Note E)








Figure 11: Normalized Maximum Transient Thermal Impedance (Note E)

Gate Charge Test Circuit & Waveform

Resistive Switching Test Circuit & Waveforms

Diode Recovery Test Circuit & Waveforms
