

### **MDA Series**

# SMD Low Profile High Current Molded Inductor

Size 1870


#### **FEATURES**


- Shielded construction
- Capable of corresponding high frequency.
- Low loss realized with low DCR.
- High performance (Isat) realized by metal dust core.
- Ultra low buzz noise, due to composite construction.
- 100% Lead(Pb)-Free and RoHS compliant.
- High reliability -Reliability test complied to AEC-Q200
- Operating temperature: -55 to +155 °C (including self-temperature rise)
- Quantity: 200PCS





- Headlamps, tail lamps and interior lighting
- HVAC
- Doors, window lift and seat control
- Audio subsystem
- Digital instrument cluster
- In-Vehicle Infotainment and navigation

## Dimensions: [mm]









Land Pattern: [mm]

### **Electrical Properties:**

| Part No      | Inductance<br>@ 100KHz/1V<br>(μH) | Tolerance | Temperature<br>Rise Current<br>Typ.<br>(A) | Saturation<br>Current<br>Typ.<br>(A) | DC<br>Resistance<br>Typ.<br>(mΩ) | DC<br>Resistance<br>Max.<br>(mΩ) |
|--------------|-----------------------------------|-----------|--|--------------------------------------|----------------------------------|----------------------------------|
| MDA1870-6R8M | 6.80                              | ±20%      | 24.0                                       | 25.0                                 | 6.00                             | 7.20                             |

Saturation Current will cause L to drop approximately 30%

Temperature Rise Current: The actual value of DC current when the temperature rise is △T=40°C